



Accessory Worksheet

NEMA Full-voltage Starter/Contactor Accessories

Use this worksheet to help identify the accessory part numbers for starter/contactor.

1 Replacement coils

Coil Voltage	Size 00	Size 0	Size 1	Size 2
24 Vac	9998SAC23	31041-400-20	31041-400-20	31063-409-16
120 Vac	9998SAC45	31041-400-42	31041-400-42	31063-409-38
208 Vac	9998SAC52	31041-400-48	31041-400-48	31063-409-44
240 Vac	9998SAC54	31041-400-51	31041-400-51	31063-409-47
480 Vac	9998SAC62	31041-400-60	31041-400-60	31063-409-57

2 Separate enclosure with reset button (enclosure suitable for starter with melting alloy or solid state overload relay only)

	Size 00	Size 0	Size 1	Size 2
NEMA Type 1	9991SCG8 ^[1]	9991SCG8 ^[1]	9991SCG8 ^[1]	9991SDG8 ^[1]
NEMA Type 12	9991SCA11	9991SCA11	9991SCA11	9991SDA11

^[1] Purchase 9999SG2 closing plate for use with 8502 contactors.

3 Push button kits

	Size 00	Size 0	Size 1	Size 2
Start/Stop NEMA 1	9999SA2	9999SA2	9999SA2	9999SA2
Start/Stop NEMA 3R/12	9999SA3	9999SA3	9999SA3	9999SA3
On/Off NEMA 1	9999SA10	9999SA10	9999SA10	9999SA10
On/Off NEMA 3R/12	9999SA3	9999SA3	9999SA3	9999SA3

4 Selector switch kits

	Size 00	Size 0	Size 1	Size 2
HOA NEMA 1	9999SC2	9999SC2	9999SC2	9999SC2
HOA NEMA 3R/12	9999SC8	9999SC8	9999SC8	9999SC8
On/Off NEMA 1	9999SC22	9999SC22	9999SC22	9999SC22

Make the most of your energySM



5 Pilot light kit


	Size 00	Size 0	Size 1	Size 2
NEMA 1	9999SP2R	9999SP2R	9999SP2R	9999SP3R
NEMA 3R/12	9999SP28R	9999SP28R	9999SP28R	9999SP28R

6 Auxiliary contact (one normally open and one normally closed field convertible contact: 9999SX8 [all sizes])

Still need help, call 888-SquareD (1-888-778-2733)

Schneider Electric - North American Operating Division

Automation and Control Center of Excellence
 8001 Knightdale Boulevard
 Knightdale, NC 27545
 Tel: 919-266-3671
 www.schneider-electric.us

 This document has been printed on recycled paper