

JUMPER SETTING

CONNECTOR	FUNCTION
JP1, JP2	AT K/B CONNECTOR
JP3, JP14	K/B CONNECTOR
JP6, JP7, JP8	FAN CONNECTOR
JP4	AT POWER CONNECTOR
JP5	POWER TERMINAL BLOCK
JP13	WAKE UP CONNECTOR
JP12	ATX POWER ON/OFF CONNECTOR
JP9	ATX POWER ON/OFF SW SELECT
S1	ATX POWER ON/OFF SW
JP10, JP11	POWER CONNECTOR
CN1	ATX POWER CONNECTOR
JP9	1-2 push button switch 2-3 push button switch with lock
JP12	1-2 push button switch 2-3 push button switch with lock

PIN DEFINITION

◆ K/B CONNECTOR

PIN Number	Description
1	CLK
2	DATA
3	NC
4	GND
5	+5V

◆ **FAN CONNECTOR**

PIN Number	Description
1	+12V
2	GND
3	NC

◆ **WAKE UP CONNECTOR**

PIN Number	Description
1	+5VSB
2	GND
3	POWER ON

◆ **ATX POWER ON/OFF CONNECTOR**

PIN Number	Description
1	Push Button Switch
2	Ground
3	Push Button Switch with lock

◆ **POWER CONNECTOR**

PIN No.	Description	PIN No.	Description	PIN No.	Description
1	NC	2	+5V	3	+12V
4	-12V	5	GND	6	GND
7	GND	8	GND	9	-5V
10	+5V	11	+5V	12	+5V
13	+5VSB	14	POWER ON	15	GND
16	GND	17	+3.3V	18	+3.3V

◆ **POWER TERMINAL BLOCK**

PIN Number	Description
1	+5V
2	-5V
3	-12V
4	+12V
5	GND