

MULTI-I/O

J39 - Multi-I/O (COM1, COM2, Keyboard, LPT)



PCB Connector: TEKA SVC225C405M123-0 (J39)

Mating Connector: ITW-PANCON 050-050-455A

The interface to I/O serial ports (COM1/COM2), the printer port and keyboard are all terminated via the connector at **J39**. A cable, part number **CBL-247-G-1-1.0**, is available from WinSystems to adapt to the conventional I/O connectors. The pinout definition for **J39** is listed below.

(COM1) DSR	2	(COM1) RTS	4	(COM1) CTS	6	(COM1) RI	8	(COM2) DCD	10	(COM2) RXD	12	(COM2) TXD	14	(COM2) DTR	16	(COM2) GND	18	(LPT) AUTOFD	20	(LPT) ERROR	22	(LPT) INIT	24	(LPT) SLCTIN	26	(LPT) GND	28	(LPT) GND	30	(LPT) GND	32	(LPT) GND	34	(LPT) GND	36	(LPT) GND	38	(LPT) GND	40	(LPT) GND	42	(LPT) GND	44	(KEYBD) GND	46	(KEYBD) GND	48	(KEYBD) KCLK	50	(KEYBD) +5V
DCD (COM1)	2	RXD (COM1)	4	TXD (COM1)	6	DTR (COM1)	8	GND (COM1)	10	DSR (COM2)	12	RTS (COM2)	14	CTS (COM2)	16	RI (COM2)	18	STROBE (LPT)	20	PD0 (LPT)	22	PD1 (LPT)	24	PD2 (LPT)	26	PD3 (LPT)	28	PD4 (LPT)	30	PD5 (LPT)	32	PD6 (LPT)	34	PD7 (LPT)	36	ACK (LPT)	38	BUSY (LPT)	40	PE (LPT)	42	SLCT (LPT)	44	GND (KEYBD)	46	KDATA (KEYBD)	48	+5V (KEYBD)	50	

