

## ORevision Control OLong Life Cycle



# COM630-B0

### Carrier Board

#### **AUDIO FEATURES**

- · Realtek ALC655 AC97 audio codec
- 6-channel audio output
- 2W amplifier for speaker-out

#### **SERIAL ATA FEATURES**

- SATA speed up to 3Gb/s
- Four L-type connectors

#### **IDE FEATURES**

- Supports up to Ultra ATA 100
- One IDE channel supports up to 2 IDE devices

#### **BIOS FEATURES**

- FWH/LPC interface
- · Supports up to 4Mbit flash ROM
- PLCC32 socket
- Supports WP# jumper
- Carrier board ROM enable/disable function supported

#### I/O CHIP 1 FEATURES

- · Winbond 83627HG-AW controller
- · LPC interface
- · Supports Smart fan
- Default I/O port address "2eh"

#### I/O CHIP 2 FEATURES

- Fintek F81216D controller
- · LPC interface
- Supports 4 COM ports
- Supports IrDA
- Watchdog timer function
- Default I/O port address "4eh"

#### DAMAGE FREE INTELLIGENCE

- Monitors system temperature and overheat alarm
- Monitors system fan speed and failure alarm

#### **TEMPERATURE**

- Operating: 0°C to 60°C
- Non-operating: -40°C to 85°C

#### **HUMIDITY**

Operating: 10% to 90%

#### **VIBRATION**

- Amplitude: 1.5mm
- Frequency: 5-55-5Hz
- Time: 360 min per 72 cyle in each 3 axes

#### REGULATORY

EMC: EN55022, EN61000-3-2, EN61000-3-3, EN55024, FCC
Part 15 Class B

#### **REAR PANEL I/O PORTS**

- 1 mini-DIN-6 PS/2 mouse port
- 1 mini-DIN-6 PS/2 keyboard port
- 3 DB-9 serial ports
- 1 DB-15 VGA port
- 1 RJ45 LAN port
- 4 USB 2.0/1.1 ports
- · Mic-in, line-in and line-out

#### I/O CONNECTORS

- 2 connectors for 4 additional external USB 2.0/1.1 ports
- 1 connector for an external serial port
- 1 LCD brightness control connector
- 1 LVDS LCD panel connector
- 1 LCD/inverter power connector
- 1 Digital I/O connector
- 1 Digital I/O power connector
- 1 front audio connector for line-out and mic-in jacks
- 1 CD-in internal audio connector
- 1 S/PDIF-in/out connector
- 1 speaker out connector
- · 1 connector for IrDA interface
- 4 Serial ATA connectors
- 1 40-pin IDE connector
- 1 FDD connector
- 1 parallel connector (optional)
- 1 24-pin ATX power connector
- 1 4-pin 12V power connector
- 1 Wake-On-Ring connector
- 1 front panel connector
- 3 fan connectors
- 1 diagnostic LED (optional)

#### **EXPANSION SLOTS**

- 1 CompactFlash socket
- 1 PCI Express x16 (Graphics or Dual SDVO)
- 2 PCI Express x1
- 4 PCI slots (PCI 2.3, 32-bit, 33MHz)

#### **COM EXPRESS CONNECTORS**

- Two 220-pin COM Express standard connectors
- Module connector pin: Tyco 3-631849-6

#### PCB

- · 4 layers, ATX form factor
- 30.5cm (12") x 24.4cm (9.6")

#### **SAFETY**

• UL, cUL, FCC Class B, CE

#### **REAR PANEL I/O PORTS**

